

PTO/SB/05

U.S. Department of Commerce
Patent and Trademark Office
PATENT

UTILITY PATENT APPLICATION TRANSMITTAL

**Assistant Commissioner for Patents
Washington, D.C. 20231
BOX PATENT APPLICATION**

Attorney Docket No.: PA000128

Date: 10/16/00

Express Mail Label No.: EJ437701458U\$

U.S. POSTAGE
09/690673
10/16/00

Dear Sir:

Transmitted herewith for filing is the patent application of:

Inventor(s): **TECHNIQUE FOR REDUCING AVERAGE POWER CONSUMPTION IN A WIRELESS COMMUNICATIONS DEVICE**

For: ARTHUR NEUFELD.

Enclosed are:

1. ☒ Patent application (22) total pages.
2. ☒ Drawings: ☒ Formal (10) sheet(s) or ☐ Informal () sheet(s).
3. ☒ Declaration/Power of Attorney: ☐ Signed ☒ Unsigned
4. ☐ An Assignment () pages and Recordation Form Cover Sheet.
5. ☐ A Preliminary Amendment () pages.
6. ☐ Information Disclosure Statement (IDS):
 - a. ☐ PTO-1449
 - b. ☐ Copies of IDS Citations (number of citations:)
7. ☐ Other:

CLAIMS:	(a) Filed	(b) Extra Claims	Large Entity Fee	Fee Paid
Total*	22 - 20	2	x \$18 =	\$36.00
Independent**	4 - 3	1	x \$80 =	\$80.00
Multiple Dependent Claim(s): <input type="checkbox"/> No <input type="checkbox"/> Yes			\$270	\$
APPLICATION FILING FEE			\$710	\$710.00
*If the number in column a is less than 20, enter 0 in column b. **If the number in column b is less than 3, enter 0 in column b.			TOTAL FEE	\$826.00

*If the number in column a is less than 20, enter 0 in column b.

****If the number in column b is less than 3, enter 0 in column b.**

8. ☐ A check in the amount of \$_____ is enclosed to pay the filing fee.
9. ☒ Please charge Deposit Account No. 17-0026 of QUALCOMM Incorporated the amount of \$826.00. The Commissioner is hereby authorized to charge payment of any additional fees which may be required, or credit any overpayment, to said Deposit Account No. 17-0026. A duplicate of this sheet is enclosed for fee processing.
10. ☒ The Commissioner is further hereby authorized to charge to said Deposit Account No. 17-0026, pursuant to 37 CFR 1.25(b), any fee whatsoever which may become properly due or payable, as set forth in 37 CFR 1.16 to 37 CFR 1.18 inclusive, for the entire pendency of this application without specific additional authorization.

Date: 10/16/00

Signature:

George C. Pappas, Reg. No. 35,065
(858) 651-1306

QUALCOMM Incorporated
Attn: Patent Department
5775 Morehouse Drive
San Diego, California 92121-1714
Telephone: (858) 651-1179
Facsimile: (858) 658-2502

TECHNIQUE FOR REDUCING AVERAGE POWER CONSUMPTION IN A WIRELESS COMMUNICATIONS DEVICE

CROSS-REFERENCE TO RELATED APPLICATIONS

5

The present invention is related to the following application of common assignee: *Technique for Reduction of Awake Time in a Wireless Communications Device Utilizing Slotted Paging* (Application Serial No. 09/118,750, filed July 17, 1998). The '750 application is incorporated by reference herein in its entirety.

10

BACKGROUND OF THE INVENTION

I. Field of the Invention

15

The present invention relates generally to wireless communications systems. More specifically, the present invention relates to a method and system for reducing power consumption in a wireless communications device.

II. Description of the Related Art

20

Wireless communications devices (WCDs) typically operate in either an active state or a standby state. In an active state (sometimes referred to as a call state), a WCD exchanges user information on a payload traffic channel, such as a radio frequency (RF) channel used for voice and/or data calls. However, when user information is not being exchanged, a WCD operates in a standby state. In a standby state, a WCD monitors a paging channel for paging channel messages transmitted by other nodes within a wireless communications system (WCS), such as base stations, satellites, and/or other WCDs. Examples of paging channel messages include ring messages that are precursors to call initiation (i.e., active state operation), and messages that update a WCD's operational parameters.

30

One type of paging channel is a slotted paging channel. Slotted paging channels include a plurality of periodic time slots, wherein each WCD in a WCS is assigned to one of the plurality of time slots. A WCD monitors paging channel transmissions during its assigned time slot. Moreover, messages to a particular WCD are transmitted only during the time slot assigned to that particular WCD. Since a WCD may receive paging channel messages during its assigned time slot, it exists in an "awake" mode during this slot. During awake mode operation, components within a WCD are configured for paging channel message reception. A WCD typically begins awake

35

mode operation before the beginning of its assigned paging channel time slot. Furthermore, a WCD may continue to operate in this awake mode after its assigned time slot if a received paging channel message requires the WCD to perform additional actions, such as receive additional transmissions.

5 Once there are no additional active mode actions to be performed, a WCD may operate in a "sleep" mode during the interval between successive occurrences of its assigned slot. During sleep mode operation, a WCD may conserve energy by shutting off power to some of its components. For example, a WCD may halt operation of certain components used for reception and processing that are not needed during time
10 intervals when no information will be directed to that particular WCD. This halting typically "freezes" internal processes, such as counters and sequence generators. In addition, this halting may also power down certain other components.

 In WCDs that operate according to CDMA standards, such as IS-95A and IS-95B (referred to herein as IS-95 systems), information, such as paging channel traffic, is
15 sent between transmitting nodes (transmitters) and receiving nodes (receivers) in the form of symbol sequences. This information is interleaved, encoded, spread according to pseudonoise (PN) sequences, and modulated into radio frequency (RF) signals that are transmitted for reception by WCDs, such as mobile telephones. Upon reception, these signals are converted into baseband signals, despread, deinterleaved, and decoded
20 into the originally transmitted information symbol sequences.

 Transmissions between a transmitter and a receiver in a CDMA system are spread by a PN sequence in the transmitter and despread by the same PN sequence in the receiver. In IS-95 systems, these PN sequences have lengths of 2^{15} symbols ("chips") and have a chip rate of 1.228 MHz. Therefore, the PN sequence period is
25 26.667 milliseconds. For proper reception of information, PN sequence generation processes in a transmitter must be aligned with PN sequence generation processes in the receiving WCD.

 In such systems, interleaving is based on an interleaving time frame, such as 20 milliseconds in IS-95 systems. For proper reception of information in a WCD, both the
30 interleaving process at a transmitter and the deinterleaving process at the receiving WCD must be also synchronized with one another.

 In addition, a WCD needs to maintain internal synchronization between its PN sequence despread(ing) process(es) and its deinterleaving process(es). That is, when a WCD transitions from a sleep mode to an awake mode, its PN sequence despread(ing) processes and deinterleaving processes must reinitiate operation as if the WCD was
35 awake during intervening sleep mode intervals. In essence, the WCD must wake up and continue to operate as if it never missed a beat.

One technique of ensuring that such internal synchronization occurs involves employing sleep mode intervals that are equal in time to an integer multiple of both the interleaving time frame and the PN sequence period. According to this approach, when a WCD transitions from a sleep mode to an awake mode, its processes resume operation at the same points in the PN sequences and interleaving frames in which they were operating when the preceding transition to sleep mode occurred. In addition, since this transition occurs at an integer multiple of both the interleaving time frame and the PN sequence period, these processes are internally synchronized.

The smallest integer multiple of both the interleaving time frame and the PN sequence period is their least common multiple. In the case of IS-95 systems, this least common multiple equals 80 milliseconds (i.e., three times the 26.667 millisecond PN sequence period and four times the 20 millisecond interleaving time frame). Conventional approaches to sleep and awake mode timing employ this least common multiple approach. Therefore, in IS-95 systems, sleep mode intervals according to this approach are constrained to a coarse granularity of 80 milliseconds.

For a WCD powered by a battery or a fixed energy source, time in a standby state can be increased by reducing the device's average current consumption. One way to achieve this reduction is to increase the duration of the sleep mode interval while reducing the duration of the awake mode interval. Generally, the fraction of time spent in an awake mode is much smaller than the amount of time spent in a sleep mode. However, since current consumed in an awake mode is generally several times greater than the current consumed during a sleep mode, any reduction in the amount of time spent in the awake mode can result in a significant improvement in current consumption and standby time.

Accordingly, what is needed is a technique that reduces the amount of time a WCD spends in an awake mode, thereby increasing the device's operational time.

SUMMARY OF THE INVENTION

The present invention is directed to a system and method for extending the operational time of a WCD, wherein the WCD is capable of operating in sleep and awake modes while monitoring a slotted paging channel. A method of the present invention comprises the steps of distributing a plurality of counters so that each counter rolls over at a predetermined offset relative to each other counter; providing a plurality of timing points that occur at the roll over times for the plurality of counters; and transitioning between sleep and awake mode operation at the occurrence of one of the plurality of timing points.

The distributing step may include the step of spacing each of the plurality of counters at substantially equal time increments around a PN sequence period. This step may also include the step of synchronizing each of the plurality of counters to a corresponding pseudonoise (PN) sequence generator. Such synchronization involves
5 shifting each of the corresponding PN sequence generators by an offset, thereby enabling the demodulation of a corresponding multipath transmission component.

The transitioning step may include the step of commencing awake mode operation at a predetermined number of timing points before the beginning of a paging channel slot assigned to the WCD. For instance, this step may involve commencing
10 awake mode operation two timing points before the beginning of such a paging channel slot.

Moreover, the transitioning step may include the step of commencing sleep mode operation at a predetermined number of timing points after the beginning of a paging channel slot that is assigned to the WCD. In addition, this step may include the
15 step of commencing sleep mode operation at a first occurring timing point after the WCD determines that there is no paging traffic to decode during such a paging channel slot.

The present invention advantageously achieves a finer granularity of sleep mode interval durations, thereby extending the length of sleep mode intervals and increasing
20 WCD operational time.

The present invention also advantageously maintains the quality of received signals. Some approaches extend sleep mode interval durations to a certain degree by removing a demodulation finger from the WCD demodulation process. Such removal of demodulation fingers may degrade the quality of received signals. In contrast, the
25 present invention maintains signal quality by retaining all demodulation fingers in the demodulation process.

BRIEF DESCRIPTION OF THE DRAWINGS

30 The present invention will be described with reference to the accompanying drawings. In the drawings, like reference numbers generally indicate identical, functionally similar, and/or structurally similar elements. The drawing in which an element first appears is indicated by the leftmost digit(s) in the reference number.

FIG. 1 is an illustration of an exemplary wireless communications system
35 (WCS);

FIG. 2 is a illustration of an exemplary paging channel frame;

FIG. 3A is a functional block diagram of an exemplary slotted paging channel receiving portion of a WCD;

FIG. 3B is an illustration of demodulation module;

FIGs. 4A and 4B are phasor diagrams that illustrate timing relationships according to two different finger timing schemes;

FIG. 5 is a flowchart illustrating an idle state operation of a WCD;

5 FIG. 6 is a flowchart illustrating an operation of entry into sleep mode operation;

FIG. 7 is a flowchart illustrating an operation of a transition into awake mode operation;

FIG. 8 is a flowchart illustrating a method of extending the operational time of a WCD; and

10 FIG. 9 is a block diagram of an exemplary computer system.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

I. Introduction

15

The present invention is directed to a technique for achieving finer granularity of sleep mode interval durations over conventional techniques. This finer granularity is achieved through the use of timing points that provide a WCD with more frequent opportunities to transition between sleep and awake mode operation. As a result of this finer granularity, a WCD may extend the length of sleep mode intervals, thereby increasing its operational time. These timing points are based on counters, such as demodulation finger counters and combiner counters, as will be described herein with reference to an exemplary WCD.

20

25 II. Wireless Communications System

FIG. 1 is an illustration of an exemplary wireless communications system (WCS) 100. Exemplary WCS 100 includes first and second base stations 102a and 102b, a wireless communications device (WCD) 106, and a system controller 108.

30

In many WCSs, multipath transmissions occur. Multipath transmissions are individual RF wavefronts, also referred to herein as multipath components, that stem from a transmission by a single RF transmitter. Multipath transmission may be caused by wavefront reflections as well as other physical occurrences. To a receiving device, such as WCD 106, each multipath component appears identical, except for a distinct time shift, and usually a different signal strength. In a CDMA system, if these multipath component time shifts are greater than the duration of one PN chip, then the individual multipath components can be independently distinguished and combined into a single

35

information stream. Such combining techniques may increase overall signal to noise ratios, thereby reducing the probability of symbol errors.

In IS-95 systems, paging channels carry signals that are encoded, interleaved, spread, and modulated, and transmitted by base stations 102 to WCD(s) 106.

A paging channel includes a repeating frame that is divided into a plurality of slots that have a fixed duration. FIG. 2 is an illustration of an exemplary paging channel frame 200. Paging channel frame 200 includes a plurality of paging channel slots 202. Each paging channel slot 202 has a paging channel duration 206. In IS-95 systems, paging channel slot duration 206 is 80 milliseconds. Paging channel frame 200 has a paging channel frame duration 204. As illustrated in FIG. 2, a plurality of WCDs 106 are each individually assigned to a particular paging channel slot 202. For instance, WCDs 106a, 106b, and 106e are assigned to paging channel slot 202a; WCD 106e is assigned to paging channel slot 202b; WCDs 106d and 106g are assigned to paging channel slot 202c; and so on.

III. Wireless Communications Device

FIG. 3A is a functional block diagram of an exemplary slotted paging channel receiving portion of WCD 106. As illustrated in FIG. 3A, WCD 106 includes an antenna segment 302, an analog receiver module 304, a demodulation module 306, a deinterleaver module 308, a decoder module 310, and a controller 312.

Antenna segment 302 receives radio frequency (RF) transmissions from base stations 102a and/or 102b. Antenna segment 302 forwards these transmissions as electrical signals to analog receiver module 304. In addition, antenna segment 302 may receive electrical signals for wireless transmission from a transmit power amplifier (not shown) within WCD 106. Accordingly, to enable the simultaneous transmission and reception of RF signals through a single antenna within antenna segment 302, antenna segment 302 may include a diplexer, as would be apparent to persons skilled in the relevant art(s).

Analog receiver module 304 receives electrical signals from antenna segment 302 within an RF frequency band. In addition, analog receiver module 304 down converts these RF signals into an intermediate frequency (IF) band. This down conversion may be performed by frequency down conversion techniques that are apparent to persons skilled in the relevant art(s). In an embodiment, analog receiver module 304 may also filter these IF signals in accordance with a specific bandwidth.

Moreover, analog receiver module 304 converts the IF signals into corresponding digital signals using analog to digital (A/D) conversion techniques, as would be apparent to persons skilled in the relevant art(s). This A/D conversion is

performed at a sampling rate that is an integer multiple of the pseudonoise (PN) chip rate employed in WCS 100. However, other sampling rates may also be used. After A/D conversion is performed, the resultant digitized IF signals are transferred to demodulation module 306.

5 Demodulation module 306 receives digitized IF signals from analog receiver module 304 and converts these digitized IF signals into one or more baseband information symbol sequences. Demodulation module 306 generates a plurality of baseband information symbol sequences wherein each information symbol sequence corresponds to a particular multipath transmission component. Demodulation module
10 306 combines this plurality of sequences into a single information sequence to decrease the probability of symbol errors. These sequences may be combined according to signal combining techniques known to persons skilled in the relevant art(s). Further details regarding the performance and functionality of demodulation module 306 are described herein with reference to FIG. 3B. Once these sequences are combined, demodulation
15 module 306 transfers a single information symbol sequence to deinterleaver module 308.

Deinterleaver module 308 receives a baseband information symbol sequence from demodulator module 306 and divides segments of this symbol sequence into a plurality of segments known as deinterleaver frames, wherein each deinterleaver frame
20 has a predetermined duration. IS-95 systems employ deinterleaver frames that are 20 milliseconds in duration. Deinterleaver module 308 arranges these frames according to an interleaving/deinterleaving scheme used by WCS 100, thereby producing a deinterleaved information symbol sequence. In particular, deinterleaver module 308 performs an inverse of an interleaving function performed by one or more transmitters
25 within WCS 100. Further details regarding interleaving and deinterleaving are included in IS-95A and IS-95B. Deinterleaver module 308 transfers this deinterleaved symbol sequence to decoder module 310.

Decoder module 310 receives a deinterleaved symbol sequence from deinterleaver module 308 and decodes this sequence. Decoder module 310 decodes in
30 accordance with a forward error correction coding (FEC) scheme used by WCS 100. Decoder module 310 may include a Viterbi decoder. Further details regarding Viterbi encoding and decoding are included in IS-95A and IS-95B. However, decoder module 310 may decode according to other coding schemes (e.g., cyclical and/or block error correction coding schemes) that are known to persons skilled in the relevant art(s).

35 Decoder module 310 transfers a decoded symbol sequence to controller 312. However, decoder module 310 may alternatively, or additionally, transfer decoded sequences to other component(s) (not shown) within WCD 106.

Controller 312 is operatively coupled to analog receiver module 304, demodulation module 306, deinterleaver module 308, and decoder module 310. Controller 312 receives decoded information symbol sequences from decoder module 310. These decoded information symbol sequences may comprise one or more paging messages received from WCS 100. Controller 312 generates responses to these paging messages and sends them to a transmission segment (not shown) of WCD 106 that transmits these responses to WCS 100 through antenna segment 302.

Controller 312 includes processor(s), memory, oscillator(s), clock(s), and/or counter(s) (not shown) that drive the operation of various components within WCD 106. For example, controller 312 may include an oscillator that tunes down conversion functionality within analog receiver module 304, and counters that control the timing and duration of sleep and awake mode intervals when WCD 106 is operating in an idle state. In addition, controller 312 may include counters to synchronize deinterleaving, combining, and decoding functions performed by demodulation module 306, deinterleaver module 308, and decoder module 310.

FIG. 3B is an illustration of demodulation module 306 in greater detail. Demodulation module 306 includes a searcher 330, a plurality of demodulation fingers 332, a plurality of corresponding buffers 334, a combiner 336, and a combiner counter 338. As described herein, demodulation module 306 receives a signal 320 from analog receiver module 304. Signal 320 is a digitized IF signal that may comprise a plurality of multipath components. Demodulation module 306 extracts one or more of these multipath components, and despreads them with a PN sequence to produce corresponding symbol sequences. In addition, demodulation module 306 employs buffers 334 to time align these symbol sequences for combining at combiner 336. Combiner 336 produces a combined symbol sequence 364 that is sent to deinterleaver module 308.

Searcher 330 correlates samples of signal 320 at a plurality of PN sequence offsets to acquire timing references for one or more of the plurality of multipath components. After these timing references are acquired, each of the one or more multipath components is assigned to a corresponding demodulation finger 332. FIG. 3B shows four demodulation fingers 332a through 332d. However, it would be apparent to persons skilled in the relevant art(s) that any number of demodulation fingers 332 may be used.

Each demodulation finger 332 includes a digital reception component 340, a finger counter 342, a PN sequence generator 344 and a multiplier 346. Digital reception component 340 converts signal 320 into a baseband symbol sequence. PN sequence generator 344 generates a PN sequence that is synchronized with the corresponding multipath component's PN sequence. At multiplier 346, this synchronized PN sequence

is multiplied, or correlated, with the baseband symbol sequence output by digital reception component 340 to produce a despread symbol sequence.

Within each particular demodulation finger 332, finger counter 342 increments each time a PN chip is generated by PN sequence generator 344. Finger counter 342 is a circular counter having the length of the PN sequence used by PN sequence generator 344. Thus, finger counter 342 "rolls over" every time the corresponding PN sequence generator 344 completes a PN sequence period. As illustrated in FIG. 3B, finger counter 342 and PN sequence generator 344 are shown receiving synchronization commands and/or signals from searcher 330. In a further embodiment, these commands and/or signals may be received from controller 312, as is shown in FIG. 3A.

For each demodulation finger 332, there is a corresponding buffer 334. Each buffer 334 receives a despread symbol sequence 360 from its corresponding demodulation finger 332. The output of finger counter 342 is used as a write index 362 for corresponding buffer 334. Each buffer 334 receives a despread symbol sequence that corresponds to a distinct multipath component. Since each multipath component has a different propagation delay, like-indexed symbols from each of the demodulation fingers 332 are written into the corresponding buffer 334 at different times.

Each of the buffers 334 outputs like-indexed symbols in a time-aligned manner. To achieve this time alignment, each buffer 334 has a buffer depth. This buffer depth enables the collection of symbols while delays necessary for time-alignment are incurred. This buffer depth is eight symbols. Buffer depths of any number of symbols may be employed, as would be apparent to persons skilled in the relevant art(s).

Symbol output from buffers 334 is controlled by combiner counter 338, which functions as a read index into each buffer 334. Combiner counter 338, like each finger counter 342, is a circular counter having the length of the PN sequence employed by each of the PN sequence generators 344. Combiner counter 338 is delayed by a certain number of PN chips from a particular finger counter 342. (This number is not constant, although it tends towards a fixed constant value. In the steady state, the number is constant.) This particular finger counter 342 corresponds to the demodulation finger 332 that tracks the multipath component having the smallest propagation delay (i.e., the earliest arriving multipath).

Upon output from each of the buffers 334, the time-aligned symbol sequences are summed by combiner 336, thereby producing a single symbol sequence 364. Before summation by combiner 336, each individual time aligned sequence may be weighted and/or processed in manners that optimize the quality of combined symbol sequence 364, as would be apparent to persons skilled in the relevant art(s).

IV. Finger Timing Schemes

As described herein, the sequences generated by PN sequence generators 344 are periodic, repeating sequences. Thus, the timing relationships between these sequences may be illustrated using phasor diagrams. As such, FIGs. 4A and 4B are phasor diagrams employing a clockwise rotation convention that illustrate the timing relationships between the sequences generated by PN sequence generators 344a-d according to two different finger timing schemes. As described herein, each PN sequence generator 344 is synchronized to a particular multipath component received by WCD 106 through antenna segment 302. The phasor diagrams of FIGs. 4A and 4B illustrate two different approaches for tracking the same multipath components. The approach illustrated in FIG. 4A involves PN sequences having phases that are closely clustered together. In contrast, the approach illustrated in FIG. 4B involves PN sequences having greater phase distribution.

FIG. 4A is a first phasor diagram 400 that illustrates PN sequence timing relationships according to a first approach. Phasor diagram 400 includes a PN circle 402 and a plurality of PN sequence phasors 404a-d. PN circle 402 represents a continuous cycle of PN sequences. Each of phasors 404a-d represents a PN sequence that is generated by a corresponding PN sequence generator 344. The timing relationship between phasors 404a-d within a PN sequence period time window follow a particular order. In particular, phasor 404a leads phasor 404b. In turn, phasor 404b leads phasor 404c, and phasor 404c leads phasor 404d. Accordingly, the PN sequence represented by phasor 404a is referred to herein as a leading PN sequence. Since each PN sequence is synchronized with a particular multipath component, the leading PN sequence is synchronized with the multipath component having the smallest propagation delay (i.e., the earliest arriving multipath).

FIG. 4B is a second phasor diagram 450 that illustrates PN sequence timing relationships according to a second approach. Phasor diagram 450 includes a PN circle 452 and a plurality of PN sequence phasors 454a-d. PN circle 452 represents a continuous cycle of PN sequences. Each of phasors 454a-d represents a PN sequence that is generated by a corresponding PN sequence generator 344.

Unlike phasors 404, which are clustered together, each phasor 454 is separated by substantially 90 degrees (i.e., one-quarter of a PN sequence period). Despite this greater phase separation, the PN sequences represented by phasors 454a-d are also able to track the same multipath components that are tracked in the approach described above with reference to FIG. 4A. This tracking of multipath components despite this 90 degree phase separation is enabled through PN sequence shifting techniques.

PN sequence shifting techniques allow a PN sequence to be shifted by a desired number of PN chips. A PN sequence generator 344 may instantaneously produce a shift upon the input of a shift mask. Further details regarding PN sequence shifting techniques and shift masks are described in U.S. Patent No. 5,228,054, entitled "Power-of-Two Length Pseudo-Noise Sequence Generator with Fast Offset Adjustment," issued 5 July 13, 1993, assigned to the assignee of the present invention (incorporated herein by reference in its entirety). For a particular PN sequence generator 344, shifting the corresponding PN sequence does not affect when corresponding finger counter 342 rolls over. Therefore, phasors 454 maintain their phase separation notwithstanding the PN 10 sequence shift.

Combiner counter 338 is synchronized to a finger counter 342. For example, combiner counter 338 may be delayed by a predetermined number of PN chips from a finger counter 342 that corresponds to a leading PN sequence, as described herein with reference to FIGs. 4A and 4B. Combiner counter 338 rolls over once every PN 15 sequence period (e.g., once every 26.667 milliseconds in IS-95 systems).

At a certain moment, combiner counter 338 may be resynchronized to another of finger counters 342. While still rolling over once every PN sequence period, a resynchronized combiner counter 338 will roll over at moments that are shifted in time by a certain amount.

Accordingly, when WCD 106 operates according to the finger timing scheme described herein with reference to FIG. 4A, a resynchronization of combiner counter 338 will create a shift in its roll over times. This shift will have a magnitude that is commensurate with multipath component delays. These magnitudes result from finger 20 counters 342 being clustered together on PN circle 402.

In contrast, when WCD 106 operates according to the finger timing scheme described herein with reference to FIG. 4B, a resynchronization of combiner counter 338 will create a greater shift in its roll over times. Such substantial shifts will occur because finger counters 342 are distributed in phase across PN circle 452. For example, in FIG. 4B, where phasors 454 represent four distinct finger counters 342 distributed in 25 a substantially equal time increments across PN circle 452, a finger counter 342 "rolls over" approximately once every quarter of a PN sequence period (e.g., once every 6.667 milliseconds in IS-95 systems).

V. Sleep and Awake Mode Transitions

WCD 106 employs the finger timing scheme as described herein with reference to FIG. 4B. Accordingly, a plurality of phasors are distributed in a substantially equal manner across PN circle 452. Each phasor represents a PN sequence generated by a corresponding finger counter 342. In a particular implementation of this timing scheme, four finger counters 342 are phase distributed in a substantially equal manner across PN circle 452. Thus, according to this implementation, a finger counter 342 rolls over approximately once every fourth of a PN sequence period (e.g., once every 6.667 milliseconds in IS-95 systems).

Combiner counter 338 is synchronized to a particular finger counter 342. Combiner counter 338 is delayed by a certain number of PN chips from a particular finger counter 342. This particular finger counter 342 may correspond to a PN sequence generator 344 generating a leading PN sequence.

FIG. 5 is a flowchart illustrating an operation of WCD 106 during idle state. This operation begins with a step 502. In this step, WCD 106 is powered on. WCD 106 may be powered with a finite energy source, such as a battery.

Next, in a step 504, analog receiver module 304 is initialized. This step comprises the steps of locking frequency synthesizers used for downconversion, locking gain scaling loops, and locking DC bias loops. These steps enable analog receiver module 304 to generate valid baseband signals from RF signals received through antenna segment 302. Performance of step 504 requires an initialization time.

A step 506 follows the performance of step 504. In step 506, searcher 330 searches PN offsets to find multipath transmission components. Step 506 comprises the step of, determining at each PN sequence offset whether a multipath component exists. This step may be performed with signal processing techniques as would be apparent to persons skilled in the relevant art(s).

In a step 508, WCD 106 assigns each of the strongest multipath components identified in step 506 to a corresponding demodulation finger 332. In an embodiment, step 508 comprises the step of, for each demodulation finger 332, synchronizing PN sequence generator 344 and finger counter 342 to enable the despreading of the assigned multipath component.

Base stations 102 transmit sync channel(s) that enable WCDs 106 to achieve system synchronization. Thus, in a step 510, WCD 106 acquires and decodes a sync channel, thereby achieving synchronization with WCS 100.

In a step 512, WCD 106 initializes combiner counter 338. Step 512 comprises the step of setting combiner counter 338 to synchronously track a finger counter 342 at

a predetermined delay equal to a number of PN sequence chips. This predetermined delay may be set to equal the depth of buffers 334.

A step 514 follows the performance of step 512. In step 514, WCD 106 shifts the sequences generated by PN sequence generators 344. This shifting is performed in accordance with the timing scheme described herein with reference to FIG. 4B. Step 514 may be performed by demodulation module 306 in conjunction with controller 312.

Next, in a step 516, WCD 106 decodes a paging channel. This step comprises the step of receiving base station originated messages that comprise a plurality of symbols. Reception of these messages includes obtaining signals through antenna segment 302, and converting these signals into a symbol stream through the operation of analog receiver module 304, demodulation module 306, deinterleaver module 308, and decoder module 310. Step 516 further comprises the steps of controller 312 receiving this symbol stream and identifying any component paging channel messages.

After performance of step 516, WCD 106 proceeds to process any received paging channel messages. In a step 518, WCD 106 determines whether a received paging message necessitates a transition into the active state. If so, operation proceeds to a step 540 for active state processing. Otherwise, operation proceeds to step 520 for further idle state processing. A ring message that notifies WCD 106 of an incoming call is an example of a paging channel message that necessitates such a transition into the active state. Step 518 is performed by controller 312.

A step 520 follows the performance of step 518. In step 520, WCD 106 determines whether there is additional paging traffic to decode. Thus, step 520 may comprise the step of determining whether a received paging channel message indicates that a further message is to be received. If there is an additional paging message to receive, steps 516 through 520 are preformed again. Otherwise, operation proceeds to a step 522.

In step 522, WCD 106 enters the sleep mode for a specific time interval. This specific time interval is greater than sleep intervals employed by conventional WCDs. This reduces battery drain and advantageously extends the operational time of WCD 106. The performance of step 522 is described in greater detail herein with reference to FIG. 6.

After performance of step 522, a step 524 follows. In step 524, WCD 106 transitions into awake mode operation. Step 524 is described in greater detail herein with reference to FIG. 7. Once this transition into awake mode operation is complete, steps 516 through 524 are repeated. This cycle continues until WCD 106 either transitions into the active state, or is powered down.

VI. Sleep Mode Interval Timing

Combiner counter 338 may change the finger counter 342 to which it is
 5 synchronized. By employing this resynchronization feature with the finger timing
 scheme described herein with reference to FIG. 4B, the duration of WCD 106 sleep
 mode intervals may be controlled with greater precision than in conventional
 approaches. This greater precision enables WCD 106 to operate with longer sleep mode
 intervals, thereby extending its operational time.

10 When WCD 106 sleeps for a non-integer multiple of the PN sequence period,
 each phasor 454 is effectively "frozen" for the duration of the sleep interval. Upon a
 subsequent reentry into awake mode operation, each phasor 454 is effectively "rotated"
 about PN circle 452. For example, in an embodiment where demodulation module 306
 employs four demodulation fingers 332, each separated at one quarter of a PN sequence
 15 period, if WCD 106 enters sleep mode operation for one quarter of a PN sequence
 period, then PN sequence generators 344 and finger counters 342 would be frozen for
 one quarter of a PN sequence period. Upon reentry of WCD 106 into awake mode
 operation, PN sequence generators 344 and finger counters 342 would be "rotated
 backwards" one quarter of a PN sequence period.

20 According to one approach, continued operation according to the
 synchronization of combiner counter 338 to the finger counter 342 employed during the
 previous awake mode would require the finger counter 342 and corresponding PN
 sequence generator 344 to be advanced by one quarter of a PN sequence period.
 However, since combiner counter 338 may change the finger counter 342 to which it is
 25 synchronized, the present invention eliminates the need to advance PN sequence
 generators 344 and finger counters 342 upon transitions into active mode operation.

FIG. 6 is a flowchart illustrating an operation of step 522 in greater detail. As
 described herein with reference to FIG. 5, in step 522, WCD 106 enters sleep mode
 operation for a specific time interval.

30 In a step 602, WCD 106 halts the operation of PN sequence generators 344,
 finger counters 342, and combiner counter 338. Once halted, the states of these
 components are frozen until a subsequent transition into awake mode operation. This
 step may be performed by controller 312. This halting occurs at the next occurrence of
 a finger counter 342 rollover. In an embodiment that employs the timing scheme
 35 described herein with reference to FIG. 4B, this halting step may be performed one
 quarter of a PN sequence period after the reception of one or more deinterleaver frames.
 In IS-95 systems, a deinterleaver frame is 20 milliseconds, and one quarter of a PN
 sequence period is 6.667 milliseconds.

Next, in a step 604, WCD 106 powers down certain electronic components for a sleep mode interval that lasts until a predetermined time before the beginning of the next paging channel slot 202 assigned to WCD 106. This predetermined time is needed to initialize components, such as decoder module 310, to proper operational states by providing them with information symbols. This predetermined time occurs at finger counter 342 rollover. In an embodiment employing the timing scheme described herein with reference to FIG. 4B, this rollover occurs at one half of a PN sequence period (13.333 milliseconds in IS-95 systems) before the beginning of the next paging channel slot 202 assigned to WCD 106.

FIG. 7 is a flowchart illustrating an operation of step 524 in greater detail. As described herein with reference to FIG. 5, in step 524, WCD 106 transitions into an awake mode.

Step 524 commences with a step 702. In step 702, WCD 106 turns on analog receiver module 304. This step comprises the steps of locking frequency synthesizer(s) used for downconversion, locking gain scaling loop(s), and locking DC bias loop(s). These steps enable analog receiver module 304 to generate valid baseband signals from RF signals received through antenna segment 302.

Next, in a step 704, WCD 106 searches the signal stream provided by analog receiver module 304 to identify multipath components. Step 704 is performed by searcher 330 of demodulation module 306. Since multipath propagation delays do not typically change rapidly, performance of step 704 may not require searching each PN offset. Instead, step 704 may comprise searching a plurality of PN offsets within a predetermined range from a previously employed PN offset.

In a step 706, WCD 106 assigns multipath components identified in step 704 to demodulation fingers 332.

After the performance of step 706 has been completed, WCD 106 enters awake mode operation, as illustrated in step 708. Awake mode operation 708 comprises a step 710 of resynchronizing combiner counter 338 to a finger counter 342 of another demodulation finger 332.

As described herein with reference to FIG. 6, awake mode operation 708 may commence one half of a PN sequence period before the beginning of the paging channel slot 202 assigned to WCD 106. To achieve this with the timing scheme described herein with reference to FIG. 4B, step 710 comprises the step of resynchronizing combiner counter 338 to a finger counter 342 that is out of phase by one-half of a PN sequence period (e.g., 13.333 milliseconds in IS-95 systems).

VII. A Method of Operational Time Extension

As described herein, the present invention enables sleep mode interval durations to be controlled with finer granularity. As a result of this finer granularity, these durations may be increased, thereby extending the operational time of a WCD.

FIG. 8 is a flowchart illustrating a method of extending the operational time of a WCD, such as WCD 106. This method begins with a step 802. In step 802, a plurality of counters, such as finger counters 342, are distributed so that each counter rolls over at a predetermined offset relative to each other counter. Step 802 comprises the step of spacing each of the plurality of counters at substantially equal time increments around a PN sequence period. For example, four counters may be spaced at one quarter PN sequence period increments, as described herein with reference to FIG. 4B.

Step 802 comprises the step of synchronizing each of the plurality of counters to a corresponding sequence generator, such as a PN sequence generator 344, as described herein with reference to FIG. 3B. This synchronizing step may comprise the step of shifting each of the corresponding sequence generators by an offset. As described herein with reference to FIG. 4B, this shifting step enables the sequence generator to demodulate a corresponding multipath transmission component.

In a step 804, a plurality of timing points are provided that occur at the roll over times for the plurality of counters that are distributed in step 802.

In a step 806, WCD 106 transitions between sleep and awake mode operation at the occurrence of one of the plurality of timing points provided in step 804.

Step 806 comprises the step of commencing awake mode operation at a predetermined number of timing points before the beginning of a paging channel slot assigned to WCD 106.

In a further embodiment, step 806 may comprise the step of commencing sleep mode operation at a predetermined number of timing points after the beginning of a paging channel slot assigned to WCD 106. This timing point may be the first occurring timing point after WCD 106 determines that there is no paging traffic to decode during a paging channel slot assigned to it.

VIII. Implementation

The functionality described herein may be implemented using hardware, software or a combination thereof and may be implemented in a computer system or other processing system. In fact, in one embodiment, the invention is directed toward a computer system capable of carrying out the functionality described herein. An

exemplary computer system 901 is shown in FIG. 9. Computer system 901 includes one or more processors, such as a processor 904. The processor 904 is connected to a communication bus 902. Various software embodiments are described in terms of this example computer system. After reading this description, it will become apparent to
5 persons skilled in the relevant art how to implement the invention using other computer systems and/or computer architectures.

Computer system 902 also includes a main memory 906, preferably random access memory (RAM), and can also include a secondary memory 908. The secondary memory 908 can include, for example, a hard disk drive 910 and/or a removable storage
10 drive 912, representing a floppy disk drive, a magnetic tape drive, an optical disk drive, etc. The removable storage drive 912 reads from and/or writes to a removable storage unit 914 in a well known manner. Removable storage unit 914, represents a floppy disk, magnetic tape, optical disk, etc. which is read by and written to by removable storage drive 912. As will be appreciated, the removable storage unit 914 includes a
15 computer usable storage medium having stored therein computer software and/or data.

In alternative embodiments, secondary memory 908 may include other similar means for allowing computer programs or other instructions to be loaded into computer system 901. Such means can include, for example, a removable storage unit 922 and an interface 920. Examples of such can include a program cartridge and cartridge interface
20 (such as that found in video game devices), a removable memory chip (such as an EPROM, or PROM) and associated socket, and other removable storage units 922 and interfaces 920 which allow software and data to be transferred from the removable storage unit 922 to computer system 901.

Computer system 901 can also include a communications interface 924.
25 Communications interface 924 allows software and data to be transferred between computer system 901 and external devices. Examples of communications interface 924 can include a modem, a network interface (such as an Ethernet card), a communications port, a PCMCIA slot and card, etc. Software and data transferred via communications interface 924 are in the form of signals which can be electronic, electromagnetic, optical
30 or other signals capable of being received by communications interface 924. These signals 926 are provided to communications interface via a channel 928. This channel 928 carries signals 926 and can be implemented using wire or cable, fiber optics, a phone line, a cellular phone link, an RF link and other communications channels.

In this document, the terms "computer program medium" and "computer usable
35 medium" are used to generally refer to media such as removable storage device 912, a hard disk installed in hard disk drive 910, and signals 926. These computer program products are means for providing software to computer system 901.

Computer programs (also called computer control logic) are stored in main memory and/or secondary memory 908. Computer programs can also be received via communications interface 924. Such computer programs, when executed, enable the computer system 901 to perform the features of the present invention as discussed herein. In particular, the computer programs, when executed, enable the processor 904 to perform the features of the present invention. Accordingly, such computer programs represent controllers of the computer system 901.

In an embodiment where the invention is implemented using software, the software may be stored in a computer program product and loaded into computer system 901 using removable storage drive 912, hard drive 910 or communications interface 924. The control logic (software), when executed by the processor 904, causes the processor 904 to perform the functions of the invention as described herein.

In another embodiment, the invention is implemented primarily in hardware using, for example, hardware components such as application specific integrated circuits (ASICs). Implementation of the hardware state machine so as to perform the functions described herein will be apparent to persons skilled in the relevant art(s).

In yet another embodiment, the invention is implemented using a combination of both hardware and software. Examples of such combinations include, but are not limited to, microcontrollers.

IX. Conclusion

While various embodiments of the present invention have been described above, it should be understood that they have been presented by way of example only, and not limitation. Thus, the breadth and scope of the present invention should not be limited by any of the above-described exemplary embodiments, but should be defined only in accordance with the following claims and their equivalents.

WHAT IS CLAIMED IS:

1. A method of reducing average power consumption in a wireless communication
2 device (WCD), the WCD operating in sleep and awake modes during monitoring of a
slotted paging channel, comprising:

4 providing a plurality of counters;
establishing a roll over point for each counter at a predetermined offset relative
6 to each other counter;
identifying a timing point for at least one roll over point; and
8 transitioning between the sleep and awake modes during the occurrence of an
identified timing point.

2. The method of claim 1, wherein establishing a roll over point comprises spacing
2 each of the plurality of counters at substantially equal time increments around a PN
sequence period.

3. The method of claim 1, wherein establishing a roll over point comprises
2 synchronizing each of the plurality of counters to a corresponding pseudonoise (PN)
sequence generator.

4. The method of claim 3, wherein synchronizing each of the plurality of counters
2 to a corresponding pseudonoise (PN) sequence generator comprises shifting each of the
corresponding PN sequence generators by an offset, thereby enabling the demodulation
4 of a corresponding multipath transmission component.

5. The method of claim 1, wherein transitioning between the sleep and awake
2 modes comprises commencing awake mode operation at a predetermined number of
timing points before the beginning of a paging channel slot assigned to the WCD.

6. The method of claim 1, wherein transitioning between the sleep and awake
2 modes comprises commencing sleep mode operation at a predetermined number of
timing points after the beginning of a paging channel slot assigned to the WCD.

7. The method of claim 1, wherein transitioning between the sleep and awake
2 modes comprises commencing awake mode operation two timing points before the
beginning of a paging channel slot assigned to the WCD.

8. The method of claim 1, wherein transitioning between the sleep and awake
2 modes comprises commencing sleep mode operation at a first occurring timing point
after the WCD determines there is no paging traffic to decode during a paging channel
4 slot assigned to the WCD.

9. The method of claim 1, wherein the slotted paging channel carries code division
2 multiple access (CDMA) signals.

10. The method of claim 9, wherein the slotted paging channel operates in
2 accordance with IS-95.

11. A Wireless Communications Device (WCD) with reduced power consumption,
2 the WCD operating in sleep and awake modes during monitoring of a slotted paging
channel, comprising:

4 a plurality of counters, each counter having a roll over point at a predetermined
offset relative to each other counter;

6 a plurality of timing points that occur at the roll over times for the plurality of
counters; and

8 a controller that transitions the WCD between sleep and awake mode operation
at the occurrence of one of the plurality of timing points.

12. The device of claim 11, wherein each of the counters are distributed at at
2 substantially equal time increments around a PN sequence period.

13. The device of claim 11, wherein each of the counters are synchronized to a
2 corresponding pseudonoise (PN) sequence generator.

14. The device of claim 13, wherein each of the corresponding PN sequence
2 generators are shifted by an offset, thereby enabling the demodulation of a
corresponding multipath transmission component.

15. The device of claim 11, wherein the controller commences awake mode
2 operation at a predetermined number of timing points before the beginning of a paging
channel slot assigned to the WCD.

16. The device of claim 11, wherein the controller commences sleep mode operation
2 at a predetermined number of timing points after the beginning of a paging channel slot
assigned to the WCD.

17. The device of claim 11, wherein the controller commences awake mode
operation two timing points before the beginning of a paging channel slot assigned to
the WCD.

18. The device of claim 11, wherein the controller commences sleep mode operation
at a first occurring timing point after the WCD determines there is no paging traffic to
decode during a paging channel slot assigned to the WCD.

19. The device of claim 11, wherein the slotted paging channel carries code division
multiple access (CDMA) signals.

20. The device of claim 19, wherein the slotted paging channel operates in
accordance with IS-95.

21. A Wireless Communications Device (WCD) with reduced power consumption,
the WCD operating in sleep and awake modes during monitoring of a slotted paging
channel, comprising:

means for providing a plurality of counters;
means for establishing a roll over point for each counter at a predetermined
offset relative to each other counter;
means for identifying a timing point for at least one roll over point; and
means for transitioning between the sleep and awake modes during the
occurrence of an identified timing point.

22. A computer program product comprising computer program logic for enabling a
processor in a computer system to reduce average power consumption in a wireless
communication device (WCD), the WCD operating in sleep and awake modes during
monitoring of a slotted paging channel, comprising:

means for enabling the processor to provide a plurality of counters;
means for enabling the processor to establish a roll over point for each counter at
a predetermined offset relative to each other counter;
means for enabling the processor to identify a timing point for at least one roll
over point; and
means for enabling the processor to transition between the sleep and awake
modes during the occurrence of an identified timing point.

ABSTRACT

5 A method and system of reducing average power consumption in a wireless
communication device (WCD) that operates in sleep and awake modes during
monitoring of a slotted paging channel includes the steps of providing a plurality of
counters; establishing a roll over point for each counter at a predetermined offset
relative to each other counter; identifying a timing point for at least one roll over point;
and transitioning between the sleep and awake modes during the occurrence of an
10 identified timing point.

11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
22




FIG. 1




FIG. 2

106





FIG. 3A






FIG. 4A




FIG. 4B




FIG. 5




FIG. 6




FIG. 7




FIG. 8

0003-25.vsd/10




FIG. 9

COMBINED DECLARATION / POWER OF ATTORNEY

ATTORNEY DOCKET NO.: PA000128

AS BELOW NAMED INVENTOR, I HEREBY DECLARE THAT: This Declaration is of the following type:

☒ Original ☐ Supplemental ☐ Continuation-In-Part ☐ Divisional
☐ Continuation ☐ National Stage of PCT

My residence, post office address and citizenship are as stated below next to my name: I believe I am the original, first and sole inventor (if only one name is listed below) or an original, first and joint inventor (if plural names are listed below) of the subject matter which is claimed and for which a patent is sought on the invention **TECHNIQUE FOR REDUCING AVERAGE POWER CONSUMPTION IN A WIRELESS COMMUNICATIONS DEVICE** the specification of which:

☒ is attached hereto.
☐ was filed on _____ US Serial No. _____
☐ was amended on _____ (if applicable).
☐ was described and claimed in PCT International Application No. _____ filed on _____ and as amended under PCT Article 19 on _____.

I hereby state that I have reviewed and understand the contents of the above-identified specification, including the claims, as amended by any amendment referred to above. I acknowledge the duty to disclose information which is material to the examination of this application in accordance with Title 37, Code of Federal Regulations, Sec. 1.56(a).

I hereby claim foreign priority benefits under Title 35, United States Code, Sec. 119 of any foreign application(s) for patent or inventor's certificate or of any PCT International application(s) designating at least one country other than the United States of America listed below and have also identified below any foreign application(s) for patent or inventor's certificate or any PCT International application(s) designating at least one country other than the United States of America filed by me on the same subject matter having a filing date before that of the application(s) of which priority is claimed.

Priority Claimed

(Country)	(Application No.)	(Day/Month/Year/Filed)	(Yes)	(No)
-----------	-------------------	------------------------	-------	------

I hereby claim the benefit under Title 35 USC 120 of the United States application(s) listed below, and insofar as the subject matter of each of the claims of this application is not disclosed in the prior United States application in the manner provided by the first paragraph of Title 35 USC 112, I acknowledge the duty to disclose material information as defined in Title 37 CFR 1.56(a) which occurred between the filing date of the prior application and the national or PCT International filing date of this application:

(Serial No.)	(Filing Date)	(Status)
--------------	---------------	----------

I hereby appoint the following attorneys and/or agents to prosecute this application and to transact all business in the U.S. Patent and Trademark Office connected therewith: Russell B. Miller, Reg. No. 31,122, Gregory D. Ogrod, Reg. No. 30,880, Bruce W. Greenhaus, Reg. No. 37,339, Charles D. Brown, Reg. No. 28,285, Thomas R. Rouse, Reg. No. 40,793, Kent D. Baker, Reg. No. 38,822, Thomas M. Thibault, Reg. No. 42,181, Tom Streeter, Reg. No. 32,007, Christopher O. Edwards, Reg. No. 36,127, Pavel Kalousek, Reg. No. 44,178, Kyong H. Macek, Reg. No. 42,977, Byron Yafuso, Reg. No. 45,244, Raymond B. Hom, Reg. No. 44,773, Kevin J. Clark, Reg. No. 42,421, Sean English, Reg. No. 37,319, Roger W. Martin, Reg. No. 39,291, Sandip S. Minhas, Reg. No. 44,945, Michael D. Hartogs, Reg. No. 36,547, Philip R. Wadsworth, Reg. No. 29,219 and S. Hossain Beladi, Reg. No. 42,311, Albert J. Harnois, Reg. No. 46,123, Sandra L. Godsey, Reg. No. 42,589, George C. Pappas, Reg. No. 35,065. Please direct all telephone calls to Philip R. Wadsworth at (858) 651-4404 and address all correspondence to: Sarah Kirkpatrick, Manager, Intellectual Property Administration, QUALCOMM Incorporated, 5775 Morehouse Drive, San Diego, California 92121-1714.

I hereby declare that all statements made herein of my own knowledge are true and that all statements made on information and belief are believed to be true; and further that these statements were made with the knowledge that willful false statements and the like so made are punishable by fine or imprisonment, or both, under Section 1001 of Title 18 of the United States Code and that such willful false statements may jeopardize the validity of the application or any patent issued thereon.

ARTHUR NEUFELD	Inventor Signature	Date
Residence 5775 Morehouse Drive, San Diego California 92121	Citizenship	
Post Office Address 5775 Morehouse Drive, San Diego California 92121		

QUALCOMM, Inc.

5775 Morehouse Drive

San Diego, California 92121-1714

Telephone: (858) 651-4404

Facsimile: (858) 658-2502